

ISSN 1726-5479

# SENSORS & TRANSDUCERS

1 vol. 136  
/12



## Sensor Instrumentation, DAQ and Virtual Instruments

International Frequency Sensor Association Publishing



**Editors-in-Chief:** Sergey Y. Yurish, tel.: +34 93 413 7941, e-mail: editor@sensorsportal.com

## Editors for Western Europe

Meijer, Gerard C.M., Delft University of Technology, The Netherlands  
Ferrari, Vittorio, Università di Brescia, Italy

## Editor for Eastern Europe

Sachenko, Anatoly, Ternopil State Economic University, Ukraine

## Editors for North America

Datskos, Panos G., Oak Ridge National Laboratory, USA  
Fabien, J. Josse, Marquette University, USA  
Katz, Evgeny, Clarkson University, USA

## Editor South America

Costa-Felix, Rodrigo, Inmetro, Brazil

## Editor for Africa

Maki K.Habib, American University in Cairo, Egypt

## Editor for Asia

Ohyama, Shinji, Tokyo Institute of Technology, Japan

## Editor for Asia-Pacific

Mukhopadhyay, Subhas, Massey University, New Zealand

## Editorial Advisory Board

- Abdul Rahim, Ruzairi, Universiti Teknologi, Malaysia  
Ahmad, Mohd Noor, Nothern University of Engineering, Malaysia  
Annamalai, Karthigeyan, National Institute of Advanced Industrial Science and Technology, Japan  
Arcega, Francisco, University of Zaragoza, Spain  
Arguel, Philippe, CNRS, France  
Ahn, Jae-Pyoung, Korea Institute of Science and Technology, Korea  
Arndt, Michael, Robert Bosch GmbH, Germany  
Ascoli, Giorgio, George Mason University, USA  
Atalay, Selcuk, Inonu University, Turkey  
Atghiaee, Ahmad, University of Tehran, Iran  
Augutis, Vyantas, Kaunas University of Technology, Lithuania  
Avachit, Patil Lalchand, North Maharashtra University, India  
Ayesh, Aladdin, De Montfort University, UK  
Azamimi, Azian binti Abdullah, Universiti Malaysia Perlis, Malaysia  
Bahreyni, Behraad, University of Manitoba, Canada  
Baliga, Shankar, B., General Monitors Transnational, USA  
Baoxian, Ye, Zhengzhou University, China  
Barford, Lee, Agilent Laboratories, USA  
Barlingay, Ravindra, RF Arrays Systems, India  
Basu, Sukumar, Jadavpur University, India  
Beck, Stephen, University of Sheffield, UK  
Ben Bouzid, Sihem, Institut National de Recherche Scientifique, Tunisia  
Benachaiba, Chellali, Universitaire de Bechar, Algeria  
Binnie, T. David, Napier University, UK  
Bischoff, Gerlinde, Inst. Analytical Chemistry, Germany  
Bodas, Dhananjay, IMTEK, Germany  
Borges Carval, Nuno, Universidade de Aveiro, Portugal  
Bousbia-Salah, Mounir, University of Annaba, Algeria  
Bouvet, Marcel, CNRS – UPMC, France  
Brudzewski, Kazimierz, Warsaw University of Technology, Poland  
Cai, Chenxin, Nanjing Normal University, China  
Cai, Qingyun, Hunan University, China  
Campanella, Luigi, University La Sapienza, Italy  
Carvalho, Vitor, Minho University, Portugal  
Cecelja, Franjo, Brunel University, London, UK  
Cerde Belmonte, Judith, Imperial College London, UK  
Chakrabarty, Chandan Kumar, Universiti Tenaga Nasional, Malaysia  
Chakravorty, Dipankar, Association for the Cultivation of Science, India  
Changhai, Ru, Harbin Engineering University, China  
Chaudhari, Gajanan, Shri Shivaji Science College, India  
Chavali, Murthy, N.I. Center for Higher Education, (N.I. University), India  
Chen, Jiming, Zhejiang University, China  
Chen, Rongshun, National Tsing Hua University, Taiwan  
Cheng, Kuo-Sheng, National Cheng Kung University, Taiwan  
Chiang, Jeffrey (Cheng-Ta), Industrial Technol. Research Institute, Taiwan  
Chiriac, Horia, National Institute of Research and Development, Romania  
Chowdhuri, Arijit, University of Delhi, India  
Chung, Wen-Yaw, Chung Yuan Christian University, Taiwan  
Corres, Jesus, Universidad Publica de Navarra, Spain  
Cortes, Camilo A., Universidad Nacional de Colombia, Colombia  
Courtois, Christian, Universite de Valenciennes, France  
Cusano, Andrea, University of Sannio, Italy  
D'Amico, Arnaldo, Università di Tor Vergata, Italy  
De Stefano, Luca, Institute for Microelectronics and Microsystem, Italy  
Deshmukh, Kiran, Shri Shivaji Mahavidyalaya, Barshi, India  
Dickert, Franz L., Vienna University, Austria  
Dieguez, Angel, University of Barcelona, Spain  
Dighavkar, C. G., M.G. Vidyamandir's L. V.H. College, India  
Dimitropoulos, Panos, University of Thessaly, Greece  
Ko, Sang Choon, Electronics. and Telecom. Research Inst., Korea South  
Kotulski, Malgorzata, Wroclaw University of Technology, Poland  
Ding, Jianning, Jiangsu Polytechnic University, China  
Djordjevic, Alexandar, City University of Hong Kong, Hong Kong  
Donato, Nicola, University of Messina, Italy  
Donato, Patricio, Universidad de Mar del Plata, Argentina  
Dong, Feng, Tianjin University, China  
Drljaca, Predrag, Intersema Sensoric SA, Switzerland  
Dubey, Venketesh, Bournemouth University, UK  
Enderle, Stefan, Univ. of Ulm and KTB Mechatronics GmbH, Germany  
Erdem, Gursan K. Arzum, Ege University, Turkey  
Erkmen, Aydan M., Middle East Technical University, Turkey  
Estelle, Patrice, Insa Rennes, France  
Estrada, Horacio, University of North Carolina, USA  
Faiz, Adil, INSA Lyon, France  
Fericean, Sorin, Balluff GmbH, Germany  
Fernandes, Joana M., University of Porto, Portugal  
Francioso, Luca, CNR-IMM Institute for Microelectronics and Microsystems, Italy  
Francis, Laurent, University Catholique de Louvain, Belgium  
Fu, Weiling, South-Western Hospital, Chongqing, China  
Gaura, Elena, Coventry University, UK  
Geng, Yanfeng, China University of Petroleum, China  
Gole, James, Georgia Institute of Technology, USA  
Gong, Hao, National University of Singapore, Singapore  
Gonzalez de la Rosa, Juan Jose, University of Cadiz, Spain  
Granel, Annette, Goteborg University, Sweden  
Graff, Mason, The University of Texas at Arlington, USA  
Guan, Shan, Eastman Kodak, USA  
Guillet, Bruno, University of Caen, France  
Guo, Zhen, New Jersey Institute of Technology, USA  
Gupta, Narendra Kumar, Napier University, UK  
Hadjiloucas, Sillas, The University of Reading, UK  
Haider, Mohammad R., Sonoma State University, USA  
Hashsham, Syed, Michigan State University, USA  
Hasni, Abdelhafid, Bechar University, Algeria  
Hernandez, Alvaro, University of Alcala, Spain  
Hernandez, Wilmar, Universidad Politecnica de Madrid, Spain  
Homontcovschi, Dorel, SUNY Binghamton, USA  
Horstman, Tom, U.S. Automation Group, LLC, USA  
Hsiai, Tzung (John), University of Southern California, USA  
Huang, Jeng-Sheng, Chung Yuan Christian University, Taiwan  
Huang, Star, National Tsing Hua University, Taiwan  
Huang, Wei, PSG Design Center, USA  
Hui, David, University of New Orleans, USA  
Jaffrezic-Renault, Nicole, Ecole Centrale de Lyon, France  
Jaime Calvo-Galleg, Jaime, Universidad de Salamanca, Spain  
James, Daniel, Griffith University, Australia  
Janting, Jakob, DELTA Danish Electronics, Denmark  
Jiang, Liudi, University of Southampton, UK  
Jiang, Wei, University of Virginia, USA  
Jiao, Zheng, Shanghai University, China  
John, Joachim, IMEC, Belgium  
Kalach, Andrew, Voronezh Institute of Ministry of Interior, Russia  
Kang, Moonho, Sunmoon University, Korea South  
Kaniusas, Eugenijus, Vienna University of Technology, Austria  
Katake, Anup, Texas A&M University, USA  
Kausel, Wilfried, University of Music, Vienna, Austria  
Kavasoglu, Nese, Mugla University, Turkey  
Ke, Cathy, Tyndall National Institute, Ireland  
Khelfaoui, Rachid, Université de Bechar, Algeria  
Khan, Asif, Aligarh Muslim University, Aligarh, India  
Kim, Min Young, Kyungpook National University, Korea South  
Sandacci, Serghei, Sensor Technology Ltd., UK  
Saxena, Vibha, Bhabha Atomic Research Centre, Mumbai, India

Kockar, Hakan, Balikesir University, Turkey  
Kong, Ing, RMIT University, Australia  
Kratz, Henrik, Uppsala University, Sweden  
Krishnamoorthy, Ganesh, University of Texas at Austin, USA  
Kumar, Arun, University of South Florida, USA  
Kumar, Subodh, National Physical Laboratory, India  
Kung, Chih-Hsien, Chang-Jung Christian University, Taiwan  
Lacnjevac, Caslav, University of Belgrade, Serbia  
Lay-Ekuakille, Aime, University of Lecce, Italy  
Lee, Jang Myung, Pusan National University, Korea South  
Lee, Jun Su, Amkor Technology, Inc. South Korea  
Lei, Hua, National Starch and Chemical Company, USA  
Li, Fengyuan (Thomas), Purdue University, USA  
Li, Genxi, Nanjing University, China  
Li, Hui, Shanghai Jiaotong University, China  
Li, Xian-Fang, Central South University, China  
Li, Yuefa, Wayne State University, USA  
Liang, Yuanchang, University of Washington, USA  
Liawruangrath, Saisunee, Chiang Mai University, Thailand  
Liew, Kim Meow, City University of Hong Kong, Hong Kong  
Lin, Hermann, National Kaohsiung University, Taiwan  
Lin, Paul, Cleveland State University, USA  
Linderholm, Pontus, EPFL - Microsystems Laboratory, Switzerland  
Liu, Aihua, University of Oklahoma, USA  
Liu Changgeng, Louisiana State University, USA  
Liu, Cheng-Hsien, National Tsing Hua University, Taiwan  
Liu, Songqin, Southeast University, China  
Lodeiro, Carlos, University of Vigo, Spain  
Lorenzo, Maria Encarnacio, Universidad Autonoma de Madrid, Spain  
Lukasiewicz, Jerzy Pawel, Nicholas Copernicus University, Poland  
Ma, Zhanfang, Northeast Normal University, China  
Majstorovic, Vidosav, University of Belgrade, Serbia  
Malyshev, V.V., National Research Centre 'Kurchatov Institute', Russia  
Marquez, Alfredo, Centro de Investigacion en Materiales Avanzados, Mexico  
Matay, Ladislav, Slovak Academy of Sciences, Slovakia  
Mathur, Prafull, National Physical Laboratory, India  
Maurya, D.K., Institute of Materials Research and Engineering, Singapore  
Mekid, Samir, University of Manchester, UK  
Melnyk, Ivan, Photon Control Inc., Canada  
Mendes, Paulo, University of Minho, Portugal  
Mennell, Julie, Northumbria University, UK  
Mi, Bin, Boston Scientific Corporation, USA  
Minas, Graca, University of Minho, Portugal  
Moghavvemi, Mahmoud, University of Malaya, Malaysia  
Mohammadi, Mohammad-Reza, University of Cambridge, UK  
Molina Flores, Esteban, Benemérita Universidad Autónoma de Puebla, Mexico  
Moradi, Majid, University of Kerman, Iran  
Morello, Rosario, University "Mediterranea" of Reggio Calabria, Italy  
Mounir, Ben Ali, University of Sousse, Tunisia  
Mrad, Nezh, Defence R&D, Canada  
Mulla, Imtiaz Sirajuddin, National Chemical Laboratory, Pune, India  
Nabok, Aleksey, Sheffield Hallam University, UK  
Neelamegam, Periasamy, Sastra Deemed University, India  
Neshkova, Milka, Bulgarian Academy of Sciences, Bulgaria  
Oberhammer, Joachim, Royal Institute of Technology, Sweden  
Ould Lahoucine, Cherif, University of Guelma, Algeria  
Pamidighanta, Sayanu, Bharat Electronics Limited (BEL), India  
Pan, Jisheng, Institute of Materials Research & Engineering, Singapore  
Park, Joon-Shik, Korea Electronics Technology Institute, Korea South  
Penza, Michele, ENEA C.R., Italy  
Pereira, Jose Miguel, Instituto Politecnico de Setebal, Portugal  
Petsev, Dimiter, University of New Mexico, USA  
Pogacnik, Lea, University of Ljubljana, Slovenia  
Post, Michael, National Research Council, Canada  
Prance, Robert, University of Sussex, UK  
Prasad, Ambika, Gulbarga University, India  
Prateepasen, Asa, Kingmoungut's University of Technology, Thailand  
Pullini, Daniele, Centro Ricerche FIAT, Italy  
Pumera, Martin, National Institute for Materials Science, Japan  
Radhakrishnan, S. National Chemical Laboratory, Pune, India  
Rajanna, K., Indian Institute of Science, India  
Ramadan, Qasem, Institute of Microelectronics, Singapore  
Rao, Basuthkar, Tata Inst. of Fundamental Research, India  
Raouf, Kosai, Joseph Fourier University of Grenoble, France  
Rastogi Shiva, K. University of Idaho, USA  
Reig, Candid, University of Valencia, Spain  
Restivo, Maria Teresa, University of Porto, Portugal  
Robert, Michel, University Henri Poincare, France  
Rezazadeh, Ghader, Urmia University, Iran  
Royo, Santiago, Universitat Politècnica de Catalunya, Spain  
Rodriguez, Angel, Universidad Politécnica de Cataluña, Spain  
Rothberg, Steve, Loughborough University, UK  
Sadana, Ajit, University of Mississippi, USA  
Sadeghian Marnani, Hamed, TU Delft, The Netherlands  
Sapozhnikova, Ksenia, D.I.Mendeleyev Institute for Metrology, Russia  
Schneider, John K., Ultra-Scan Corporation, USA  
Sengupta, Deepak, Advance Bio-Photonics, India  
Seif, Selemeni, Alabama A & M University, USA  
Seifter, Achim, Los Alamos National Laboratory, USA  
Shah, Kriyang, La Trobe University, Australia  
Sankarraj, Anand, Detector Electronics Corp., USA  
Silva Girao, Pedro, Technical University of Lisbon, Portugal  
Singh, V. R., National Physical Laboratory, India  
Slomovitz, Daniel, UTE, Uruguay  
Smith, Martin, Open University, UK  
Soleymanpour, Ahmad, Damghan Basic Science University, Iran  
Somani, Prakash R., Centre for Materials for Electronics Technol., India  
Sridharan, M., Sastra University, India  
Srinivas, Talabattula, Indian Institute of Science, Bangalore, India  
Srivastava, Arvind K., NanoSonix Inc., USA  
Stefan-van Staden, Raluca-Ioana, University of Pretoria, South Africa  
Stefanescu, Dan Mihai, Romanian Measurement Society, Romania  
Sumriddetchka, Sarun, National Electronics and Computer Technology Center, Thailand  
Sun, Chengliang, Polytechnic University, Hong-Kong  
Sun, Dongming, Jilin University, China  
Sun, Junhua, Beijing University of Aeronautics and Astronautics, China  
Sun, Zhiqiang, Central South University, China  
Suri, C. Raman, Institute of Microbial Technology, India  
Sysoev, Victor, Saratov State Technical University, Russia  
Szewczyk, Roman, Industrial Research Inst. for Automation and Measurement, Poland  
Tan, Ooi Kiang, Nanyang Technological University, Singapore  
Tang, Dianping, Southwest University, China  
Tang, Jaw-Luen, National Chung Cheng University, Taiwan  
Teker, Kasif, Frostburg State University, USA  
Thirunavukkarasu, I., Manipal University Karnataka, India  
Thumbavanam Pad, Kartik, Carnegie Mellon University, USA  
Tian, Gui Yun, University of Newcastle, UK  
Tsiantos, Vassilios, Technological Educational Institute of Kaval, Greece  
Tsigara, Anna, National Hellenic Research Foundation, Greece  
Twomey, Karen, University College Cork, Ireland  
Valente, Antonio, University, Vila Real, - U.T.A.D., Portugal  
Vanga, Raghav Rao, Summit Technology Services, Inc., USA  
Vaseashta, Ashok, Marshall University, USA  
Vazquez, Carmen, Carlos III University in Madrid, Spain  
Vieira, Manuela, Instituto Superior de Engenharia de Lisboa, Portugal  
Vigna, Benedetto, STMicroelectronics, Italy  
Vrba, Radimir, Brno University of Technology, Czech Republic  
Wandelt, Barbara, Technical University of Lodz, Poland  
Wang, Jiangping, Xi'an Shiyong University, China  
Wang, Kedong, Beihang University, China  
Wang, Liang, Pacific Northwest National Laboratory, USA  
Wang, Mi, University of Leeds, UK  
Wang, Shinn-Fwu, Ching Yun University, Taiwan  
Wang, Wei-Chih, University of Washington, USA  
Wang, Wensheng, University of Pennsylvania, USA  
Watson, Steven, Center for NanoSpace Technologies Inc., USA  
Weiping, Yan, Dalian University of Technology, China  
Wells, Stephen, Southern Company Services, USA  
Wolkenberg, Andrzej, Institute of Electron Technology, Poland  
Woods, R. Clive, Louisiana State University, USA  
Wu, DerHo, National Pingtung Univ. of Science and Technology, Taiwan  
Wu, Zhaoyang, Hunan University, China  
Xiu Tao, Ge, Chuzhou University, China  
Xu, Lisheng, The Chinese University of Hong Kong, Hong Kong  
Xu, Sen, Drexel University, USA  
Xu, Tao, University of California, Irvine, USA  
Yang, Dongfang, National Research Council, Canada  
Yang, Shuang-Hua, Loughborough University, UK  
Yang, Wuqiang, The University of Manchester, UK  
Yang, Xiaoling, University of Georgia, Athens, GA, USA  
Yaping Dan, Harvard University, USA  
Ymeti, Aurel, University of Twente, Netherland  
Yong Zhao, Northeastern University, China  
Yu, Haihu, Wuhan University of Technology, China  
Yuan, Yong, Massey University, New Zealand  
Yufera Garcia, Alberto, Seville University, Spain  
Zakaria, Zulkarnay, University Malaysia Perlis, Malaysia  
Zagnoni, Michele, University of Southampton, UK  
Zamani, Cyrus, Universitat de Barcelona, Spain  
Zeni, Luigi, Second University of Naples, Italy  
Zhang, Minglong, Shanghai University, China  
Zhang, Qintao, University of California at Berkeley, USA  
Zhang, Weiping, Shanghai Jiao Tong University, China  
Zhang, Wenming, Shanghai Jiao Tong University, China  
Zhang, Xueji, World Precision Instruments, Inc., USA  
Zhong, Haoxiang, Henan Normal University, China  
Zhu, Qing, Fujifilm Dimatix, Inc., USA  
Zorzano, Luis, Universidad de La Rioja, Spain  
Zourob, Mohammed, University of Cambridge, UK

# Contents

Volume 136  
Issue 1  
January 2012

[www.sensorsportal.com](http://www.sensorsportal.com)

ISSN 1726-5479

## Research Articles

### Digital Sensors and Sensor Systems: Practical Design

*Book Review*..... I

### Fast and Simple Measurement of Position Changes

*White Paper, iC-Haus GmbH*..... IV

### A Novel Method of Linearizing Thermistor Characteristic Using Voltage Controlled Oscillator

*Narayana K. V. L and Bhujanga Rao A*..... 1

### A Data Acquisition System Based on DSP for Mechanical Nanoscale Displacement Sensor

*Yong Yu, Qian Wu, Hanyu Sun, Zhengwei Li and Yunjian Ge* ..... 12

### Modified AC Wheatstone Bridge Network for Accurate Measurement of Pressure Using Strain Gauge Type Pressure Sensor

*Subrata Chattopadhyay, Mahuya Banerjee and Sagarika Pal*..... 25

### Fingerprint Sensors: Liveness Detection Issue and Hardware based Solutions

*Shahzad Memon, Nadarajah Manivannan, Azad Noor, Wamadeva Balachadran, Nikolaos V. Boulgouris* ..... 35

### Fiber Optic Vibration Sensor Using Pmma Fiber for Real Time Monitoring

*P. Kishore, D. Dinakar, D. Sen Gupta, P. Saidi Reddy, M. Sai Shankar, K. Srimannarayana* ..... 50

### ARM Processor Based Multisensor System Design for the Measurement of Environmental Parameters

*NarasimhaMurthy Yayavaram, Soundara Rajan, Vishnu Vardhan*..... 59

### A Decoupling Algorithm Based on Homotopy Theory for 3-D Tactile Sensor Arrays

*Junxiang Ding, Yunjian Ge, Yuan Wang, Zhaochui Wang* ..... 72

### Digital Imaging and Piezo-dispenser Actuator in Automatic Flocculation Control

*Jani Tomperi, Markus Honkanen, Pasi Kallio, Kauko Leiviskä, Pentti Saarenrinne, Iiris Joensuu, Marjatta Piironen* ..... 83

### An Embedded Web based Real Time Application for Remote Monitoring & Controlling of MST RADAR Transmitters

*Nagabhushan Raju Konduru, Lakshmi Narayana Roshanna, Rajendra Prasad Thommundru, Chandrasekhar Reddy Devanna* ..... 96

### Advanced Oscilloscope Triggering Based on Signal Frequency

*Shakeb A. Khan, Alka Nigam, A. K. Agarwala, Mini S. Thomas, T. Islam* ..... 105

### Pyramidal Traceability Hierarchy for Pressure Measurements and Calibrations at NIS- Egypt

*A. A. Eltawil*..... 118



<b>Fuzzy Logic Based Autonomous Traffic Control System</b> <i>Muhammad Abbas, M. Saleem Khan, Nasir Ali and Syed Fazil .....</i>	132
<b>Potential of Piezoelectric Sensors in Bio-signal Acquisition</b> <i>Dipali Bansal.....</i>	147
<b>Measurement and Analysis of Sodium in Vegetables Using ATmega16 Microcontroller Based Spectrophotometer</b> <i>K. Murugananthan and P. Neelamegam.....</i>	158

Authors are encouraged to submit article in MS Word (doc) and Acrobat (pdf) formats by e-mail: editor@sensorsportal.com  
Please visit journal's webpage with preparation instructions: <http://www.sensorsportal.com/HTML/DIGEST/Submition.htm>

International Frequency Sensor Association (IFSA).


## Inertial Combo Sensors for Consumer & Automotive

### Technology, Applications, Industry & Market Report to 2016

Promoted  
by  
**IFSA**

*This report is focused on the analysis of the opportunities and the challenges for inertial combo sensors in those high-volume market areas.*

[http://www.sensorsportal.com/HTML/Inertial\\_Combo\\_Sensors\\_Market.htm](http://www.sensorsportal.com/HTML/Inertial_Combo_Sensors_Market.htm)



## Uncooled Infrared Imaging Market: Commercial & Military applications

### Market & Technology Report to 2016

Promoted  
by  
**IFSA**

*This new 2011 IR report , is an updated and in depth analysis of commercial markets covered in the 2010 report in addition we have included a new analysis of the military markets.*

[http://www.sensorsportal.com/HTML/Detectors\\_for\\_Thermography.htm](http://www.sensorsportal.com/HTML/Detectors_for_Thermography.htm)



The 3rd International Conference on Sensor Device Technologies and Applications



## SENSORDEVICES 2012

19 - 24 August 2012 - Rome, Italy

Deadline for papers: 5 April 2012



**Tracks:** Sensor devices - Ultrasonic and Piezosensors - Photonics - Infrared - Geosensors - Sensor device technologies - Sensors signal conditioning and interfacing circuits - Medical devices and sensors applications - Sensors domain-oriented devices, technologies, and applications - Sensor-based localization and tracking technologies

<http://www.iaria.org/conferences2012/SENSORDEVICES12.html>

The 6th International Conference on Sensor Technologies and Applications



## SENSORCOMM 2012

19 - 24 August 2012 - Rome, Italy

Deadline for papers: 5 April 2012



**Tracks:** Architectures, protocols and algorithms of sensor networks - Energy, management and control of sensor networks - Resource allocation, services, QoS and fault tolerance in sensor networks - Performance, simulation and modelling of sensor networks - Security and monitoring of sensor networks - Sensor circuits and sensor devices - Radio issues in wireless sensor networks - Software, applications and programming of sensor networks - Data allocation and information in sensor networks - Deployments and implementations of sensor networks - Under water sensors and systems - Energy optimization in wireless sensor networks

<http://www.iaria.org/conferences2012/SENSORCOMM12.html>

The 5th International Conference on Advances in Circuits, Electronics and Micro-electronics



## CENICS 2012

19 - 24 August 2012 - Rome, Italy

Deadline for papers: 5 April 2012



**Tracks:** Semiconductors and applications - Design, models and languages - Signal processing circuits - Arithmetic computational circuits - Microelectronics - Electronics technologies - Special circuits - Consumer electronics - Application-oriented electronics

<http://www.iaria.org/conferences2012/CENICS12.html>

## An Embedded Web based Real Time Application for Remote Monitoring & Controlling of MST RADAR Transmitters

<sup>1</sup>Nagabhushan Raju KONDURU, <sup>1</sup>Lakshmi Narayana ROSHANNA,  
<sup>2</sup>Rajendra Prasad THOMMUNDRU, <sup>3</sup>Chandrasekhar Reddy DEVANNA

<sup>1</sup>Department of Instrumentation, Sri Krishnadevaraya University,  
Anantapur, 515003, India

Tel.: 08554 - 255744

<sup>2</sup>National Atmospheric Research Laboratory (NARL),  
Gadanki, 517112, India

Tel.: +91 858 527 2003, fax: +91 858 527 2018

<sup>3</sup>Megabyte Technologies, Bangalore

Tel.: +91 974 014 3321

E-mail: knrbhushan@yahoo.com, hilakshmin@yahoo.com, trp1910@narl.gov.in,  
ravichandru@mail.com

*Received: 3 November 2011 /Accepted: 24 January 2012 /Published: 30 January 2012*

---

**Abstract:** An embedded web based radar transmitters control & interlock system is developed in the present work. This research activity facilitates controlling and monitoring 53-MHz, 2.5 Mega-watt peak power MST radar triode based transmitters via internet. This radar is a prime instrument for atmospheric science research with 32 transmitters powering 1024-element antenna array. A comprehensive safety interlock is built in to protect expensive devices; by sensing anode voltages, heater currents and airflow etc. It automatically prevents fatal damages by switching transmitter / RF off. The system is designed and developed using RISC microcontroller ARM LPC 2148 based on a 32-bit ARM7 TDMI-S CPU with real-time emulation and embedded trace support and 512 kB high speed flash memory. The microcontroller is a blend of serial communication interface, dual 10-bit ADC's and fast GPIO. Ethernet controller LM3S6432 is used to send sensors' digitalized data over internet. *Copyright © 2012 IFSA.*

**Keywords:** ARM7LPC2148, MST radar transmitter, Ethernet controller LM3S6432


---



## 1. Introduction

Fundamental scientific research in atmospheric and space sciences is being conducted at NARL, Gadanki by various collocated instruments. NARL is obtaining atmospheric parameters about different atmosphere dynamical process with very high resolution instruments. Statistical description of atmospheric motions over the earth, their role in transporting the constituents of the atmosphere and the transformation of different forms of energy is studied with sophisticated MST radar [1]. The 53 MHz MST radar operating since 1991 is a prime instrument for atmospheric science research with 32 transmitters powering a 1024-element square grid antenna array. Transmitters are four stage amplifiers, with first solid-state amplifier followed by three stages of triode based amplifiers with a total gain of nearly 81 dB. The four amplifier stages in the transmitter use expensive devices, hence a web based comprehensive safety is built into the system with this embedded web based real time remote monitoring and controller to protect them against supply variations, failures, cooling etc. This system monitors the status of all the 32 radar transmitters' health parameters and automatically acts upon to safeguard the systems in case of malfunctions. System personnel can access, monitor and maintain on-site system through the network without the limit of region and time. It greatly simplifies the system testing methodology. Development of Ethernet technology facilitates the installation of remote monitoring of the transmitters and real-time performance of radar is improved. This research activity provided facility to control and monitor the MST radar transmitters via internet with this embedded web based radar transmitters control & interlock system.

The remote control and monitoring system is designed and developed using RISC microcontroller ARM LPC 2148. This microcontroller is based on a 32 bit ARM7 TDMI-S CPU with real-time emulation and embedded trace support with 512 kB high speed flash memory. It is ideal for applications like access control due to tiny size and low power consumption. The microcontroller is a blend of serial communication interface, dual 10-bit ADC's to read analog data and fast GPIO lines are used to control transmitter. Serial communication port is used to send sensors' digitalized data to web using Ethernet converter LM3S6432. This system connects the triode based transmitters to internet to control and monitor health of amplifier stages. Thus 'Embedded Web based Real Time Application for Remote Monitoring & Controlling of MST RADAR Transmitters' allows scientists to operate and control the transmitters from remote client webpage.




**Fig. 1.** Experimental setup for transmitter parameters acquisition over internet.




## 2. Hardware Description

The hardware of the ARM based centralized control and interlock system consists of LPC2148 based 16/32 bit ARM7TDMI-S™ core microcontroller board, relay driver board and LM3S6432 Ethernet controller integrated in a single unit.



**Fig. 2.** The connectivity of system and to network.


The main application, sensors analog parameters reading from transmitters is performed by ARM7TDMI-S core microcontroller that is a 64 Pin (LQFP) LPC2148 from Philips (NXP). It includes USB, ADC, DAC, timer/counter, capture, I2C, SPI, UART etc. This microcontroller consists of real-time emulation and embedded trace support. Together with 128/512 kilobytes of embedded high speed flash memory, with on-chip 4 MHz internal oscillator, 32 kB SRAM make the device very well suited for this type of applications. Various 32-bit timers, an improved 10-bit ADC, 10-bit DAC, a CAN control unit, and up to 70 fast GPIO lines with up to 12 edge or level sensitive external interrupt pins make this microcontroller particularly suitable for control systems.



**Fig. 3.** LPC 2148 ARM controller board.


Ethernet application is developed using LM3S6432 microcontroller for sending the parameter values to a central computer system. LM3S6432 is a highly integrated ARM® Cortex-M3 microcontroller with integrated 10/100 Ethernet MAC and PHY. It has efficient network traffic handling with 50-MHz performance and ample single cycle on-chip Flash and SRAM memory. This S2E module includes one

10/100 Ethernet port and two serial ports with flexibility that includes both RS-232 and CMOS/TTL level signaling, flow control, and hardware support for both synchronous and asynchronous serial communication.[3]



**Fig. 4.** The connectivity of s2e module and to network.

A 4-channel TTL relay board with 5V with solid state relays switches high-current loads of transmitter electrical systems like cathode, filament voltages, anode voltages and RF ON OFF module. The relay needs the input control signals and has no effect on the output voltage with the relay contacts. The active driver circuits allow lower current input signals such as 5V TTL to be used. The relay contacts are electrically isolated from the rest of the board, with status of each relay is indicated visually by LEDs.




**Fig. 5.** Relay card board.

MST radar transmitters have four amplifying stages and associated power monitoring and controlling and safety interlock circuits. The input to the transmitter is 1milli watt pulse-modulated (coded / uncoded) signal at 53 MHz. The output powers of the amplifiers range from 0.05-0.1 kW [SSA], 0.3-1.2 kW [PDR], 3-15 kW [DR] and 36-120 kW [HPA] and the corresponding bandwidths are 3.5, 3.2 and 2 MHz respectively; the transmitters power across the 32 numbers is in correspondence with Taylor distribution to improve antenna sidelobe level better than -20 dB. The transmitters use triodes 3CX1500, 3CPX1500 and 3CPX5000 made by Varian / CPI with triode anode voltages of the order of 2.5 kV, 5.6 kV, and 6.2 kV. These devices need precise heater voltages, currents anode voltages and cooling systems for its working. Hence a comprehensive health monitoring and control system is built in transmitter.



**Fig. 6.** The snapshot of MST radar transmitters in a building.



**Fig. 7.** Simplified radar transmitter showing RF amplifier chain, safety interlock circuits.

MST Radar transmitter triode amplifier operates in class-C mode. Heat dissipated in RF amplifier is driven away by fan/blower placed near triode (forced air-cooling system). Presence / absence of airflow are sensed by flap attached micro switch contact ON- OFF operation. Monitor voltage presence indicates obstruction in airflow and interlock operates to switch off heater, anode supply and RF switch.

Transmitter triodes' filaments/heaters are kept ON for at least 6 minutes before application of anode supply and RF signal. Filament heater current is monitored using current sensor (current transformer and associated circuits), which provides monitor dc voltage for rated heating load. Filament current drawn by the AC 5V, 5A (DR 5V, 5A and HPA 15V, 15 A) power supply is monitored using current sensors placed in the filament voltage connection to triode. If filament current is reduced due to arcing or increased triode filament resistance, filament draws less current than rated current. Interlock assumes abnormality in triode filament circuit, hence anode supply and RF OFF command are switched off. Presence / absence of anode supply in PDR (DR, HPA) RF amplifier cavity are monitored using potential divider/bleeder resistor network. This potential divider sensor provides DC voltage of about 4 V while Anode supply is ON. If the sensor voltage is less than reference voltage due to any reason, Interlock unit assumes absence of anode supply, LED indicates anode voltage absence, and RF OFF command is given to RF switch.



These analog monitoring signals are inputs of ARM microcontroller and transmitters are monitored continuously. In case of malfunction of any, the anode supplies or RF switch are operated to safeguard the transmitters.

### **3. System Functionality**

Embedded web based transmitters monitoring and controlling system directly connects each MST radar transmitter as a node to the network. The parameters measured are amplifiers, air flow, heater current, anode voltage, and SSA overload. These signals are monitored continuously and  $T_x$  are controlled. The sensed signals are fed to analog to digital converters for conversion to digital values. The ARM7LPC2148 chip controls the A/D conversions and the data transmission with ARM processor. The digitized data is displayed in the web page form by embedded web server.

Once transmitter auto operation is selected through the MAN/AUTO button on transmitter front panel for regular Tx operation, the transmitter is made sure to be ON using TX ON/OFF button on the webpage. All the heaters and HTs are powered-up automatically and the RF control is given on RF ON/OFF button. This button is used to bring the process to standby/active state only under the auto operation. In manual mode of operation, which is used for transmitter troubleshooting, it is essential that all the heaters and HTs be operated individually. These manual/auto operations are processed with the interlock parameters to evaluate the control actions. Interlock unit monitors the health condition of the heater currents, anode voltages, airflow etc. Fault status of any parameter automatically locks the concerned process and the RF transmission. During troubleshoot in the interlock section, the interlock conditions get bypassed and ARM evaluates control actions only based on the user choice. During troubleshoot in the ARM board all the relays permanently get energized in the relay driver board to continue the process.

The transmitters are connected to network via ARM processor through the RJ45 connector of Ethernet controller. The transmitters are active over the internet. The hardware can be accessible, from the remote place, by entering the IP address of the corresponding transmitter on the address bar (URL) of the internet browser.

### **4. Web Based System Description**

The remote monitoring system completes the data collection in the embedded device and provides the data to remote host through the TCP/IP protocol from web server. Web server in embedded devices performs remote monitoring, diagnosis and controlling of all nodes on the network. Embedded system is a kind of special computer system which has limited resources and functions. To implement web server running in the client system, requests are processed by the ARM embedded system. Considering the need for large dynamic data exchange during equipment monitoring and controlling, the logic is implemented through C# (C-Sharp) and ASP.Net environment. ARM embedded system is a special kind of computer system which has limited resources and functions, hence to implement web server in embedded system is characteristic of itself.

Active socket provides an easy-to-use development interface to a variety of IP protocols. By using active socket, one can very easily create or enhance applications with network features. Active socket features ICMP, HTTP and HTTPS with support for proxy servers and secure web sites, Telnet, NTP time protocol, RSH remote shell script interface, SNMP (Simple Network Management Protocol), SNMP Traps, Sockets (TCP and UDP), WOL (Wake-On-LAN) etc. Active socket can be well integrated into ASP.NET environments.

The transmitters are active over the internet. The hardware is accessible from the remote place, by entering the IP address of the corresponding transmitter on the address bar of webpage. The webpage contains the information about which transmitter is connected, transmitters health and ON/OFF control of transmitter parameters. In this webpage the RF ON/OFF button is used to switch on the RF power of transmitter. The health status of the each parameter and voltage levels are shown in Fig. 8.



Fig. 8. Screen shot of webpage contained  $T_x$  health parameter values.

Health status (good or bad) is indicated as a colour bubble. The RED is indicated as fault/bad condition of the corresponding parameter and GREEN indicates good condition. On clicking the RF ON/OFF and control ON/OFF buttons the respective command/data is sent by client browser to the server through the protocol layer of the TCP/IP stack. Then the server logically handles the data and sends to microcontroller. The web server loads transmitter current status automatically at few seconds refresh rate in webpage. ARM microcontroller will take the appropriate actions.

The software flow diagram is explained in Fig. 9. The first step is to initialize GPIO's, ADC, UART and TIMER. Timer interrupt is set to one second, hence ADC converts analog values every one second to digital form and frame a serial packet. All the parameters of the selected transmitter are placed in the serial packet in a predefined sequence. The serial packet contains STX, ETX, parameters health status and controls. The UART sends serial packet to Ethernet controller. The transmitter always sends updated data to centralized controller located at instrumentation room for webpage monitoring, transmitter status display and archival of transmitter health status.

Transmitter is controlled by the central computer with the help of ARM controller digital I/O lines. ARM read/accepts controls from webpage by Ethernet and then converts the same in serial communication mode to control transmitter via main ARM processor, to perform task corresponding to the commands from the webpage.

## 5. Results & Test Report

The design and implementation of ARM based interlock and fault monitoring system is thus carried out efficiently with advantages of high density code size, cost and power requirements. The combination of complexity and speed is finding ready applications for ARM systems in digital

processing and particularly in those application areas requiring sophisticated high speed digital control. Fig. 10 is a webpage snap shot of one of the 32 radar transmitters.  $T_x$  selection is at top left, drop down box. The webpage displays  $T_x$  output power in kW and antenna sub array health with help of reflected power indication.




Fig. 9. System software flow diagram.






Fig. 10. Webpage snapshot for selection of one transmitter out of 32 transmitters.

## 6. Conclusions

Remote monitoring and controlling system based on web technology for embedded devices is designed and implemented in this work. The system adapts browser/server mode and realizes the interconnection of the embedded devices like ARM processor target board. Therefore, remote users can access, control and manage the embedded devices [ARM processor through MST radar transmitter] using a standard web browser over the internet. It has advantages of small size, data logger, system maintenance, longer work time and stable performance. It is applicable to a variety of fields like industrial control and automation, medical instrumentation etc.

## Acknowledgement

The authors acknowledge the help and support of ISRO for grant and NARL for providing the facilities for carrying out the research work.

## References

- [1]. User Manual, Indian MST Radar Transmitter, NARL, Gadnaki.
- [2]. LPC2148 Data Sheet, ([http://www.keil.com/dd/docs/datashts/philips/lpc2141\\_42\\_44\\_46\\_48.pdf](http://www.keil.com/dd/docs/datashts/philips/lpc2141_42_44_46_48.pdf))
- [3]. Stellaris® LM3S6432 (<http://focus.ti.com/docs/prod/folders/print/lm3s6432.html>)
- [4]. The Keil µVision4 Integrated Development Environment, (<http://www.keil.com/uv4/>)
- [5]. Ethernet flash utility ([http://www.nxp.com/documents/application\\_note/AN10744.pdf](http://www.nxp.com/documents/application_note/AN10744.pdf))
- [6]. ASP. NET tutorial, (<http://www.w3schools.com/aspnet/default.asp>)
- [7]. ARM Architecture (<http://www.arm.com>)
- [8]. A. Ramakanth Gayakwad, Op-Amps and Linear Integrated Circuits, 4<sup>th</sup> edition, PHI, 2002.
- [9]. National Atmospheric Research Laboratory web portal (<http://www.narl.gov.in/>)

# GlobeNet 2012

29 February - 5 March 2012 - Saint Gilles, Reunion Island



## The Eleventh International Conference on Networks **ICN 2012**

### Wireless communications:

Satellite, WLL, 4G, Ad Hoc, sensor networks



## The Seventh International Conference on Systems **ICONS 2012**

### System Instrumentation:

Metering embedded sensors; Composing multi-scale measurements; Monitoring instrumentation; Smart sensor-based systems; Calibration and self-calibration systems; Instrumentation for prediction systems

### Specialized systems [sensor-based, etc.]:

Sensor-based systems; Biometrics systems; Nano-technology-based systems, etc.

**Deadline for papers: 5 October 2011**

<http://www.iaria.org/conferences2012/GlobeNet12.html>



# BioSciencesWorld 2012

25-29 March 2012 - St. Maarten, Netherlands Antilles

## The Fourth International Conference on Bioinformatics, Biocomputational Systems and Biotechnologies

### **BIOTECHNO 2012**

**Deadline for papers: 5 November 2011**

### Biodevices:

Biosensors; Biochips; Specialized biodevices;  
Nanotechnology for biosystems

### Biomedical technologies:

Biomedical instrumentation; Biomedical metrology and certification;  
Biomedical sensors; Biomedical devices with embedded computers;  
Biomedical integrated systems, etc.

<http://www.iaria.org/conferences2012/BioSciencesWorld12.html>

## The Third International Conference on Bioenvironment, Biodiversity and Renewable Energies

### **BIONATURE 2012**




## Mobile Advertising Solutions for Sensor Industry: How to reach 80,000+ addressable mobile audiences?



An industry first Smartphone mobile advertising solution  
for sensors manufacturers and distributors



**50% OFF**  
for limited time interval



Create your account today and use a **discount coupon code ls10001**  
to start advertising your sensors now:

[https://www.lesensor.com/sensor/Profiles/CreateNewAccount.aspx?sensor\\_portal=ls10001](https://www.lesensor.com/sensor/Profiles/CreateNewAccount.aspx?sensor_portal=ls10001)

## Guide for Contributors

---

### Aims and Scope

*Sensors & Transducers Journal* (ISSN 1726-5479) provides an advanced forum for the science and technology of physical, chemical sensors and biosensors. It publishes state-of-the-art reviews, regular research and application specific papers, short notes, letters to Editor and sensors related books reviews as well as academic, practical and commercial information of interest to its readership. Because of it is a peer reviewed international journal, papers rapidly published in *Sensors & Transducers Journal* will receive a very high publicity. The journal is published monthly as twelve issues per year by International Frequency Sensor Association (IFSA). In addition, some special sponsored and conference issues published annually. *Sensors & Transducers Journal* is indexed and abstracted very quickly by Chemical Abstracts, IndexCopernicus Journals Master List, Open J-Gate, Google Scholar, etc. Since 2011 the journal is covered and indexed (including a Scopus, Embase, Engineering Village and Reaxys) in Elsevier products.

### Topics Covered

Contributions are invited on all aspects of research, development and application of the science and technology of sensors, transducers and sensor instrumentations. Topics include, but are not restricted to:

- Physical, chemical and biosensors;
- Digital, frequency, period, duty-cycle, time interval, PWM, pulse number output sensors and transducers;
- Theory, principles, effects, design, standardization and modeling;
- Smart sensors and systems;
- Sensor instrumentation;
- Virtual instruments;
- Sensors interfaces, buses and networks;
- Signal processing;
- Frequency (period, duty-cycle)-to-digital converters, ADC;
- Technologies and materials;
- Nanosensors;
- Microsystems;
- Applications.

### Submission of papers


Articles should be written in English. Authors are invited to submit by e-mail [editor@sensorsportal.com](mailto:editor@sensorsportal.com) 8-14 pages article (including abstract, illustrations (color or grayscale), photos and references) in both: MS Word (doc) and Acrobat (pdf) formats. Detailed preparation instructions, paper example and template of manuscript are available from the journal's webpage: <http://www.sensorsportal.com/HTML/DIGEST/Submission.htm> Authors must follow the instructions strictly when submitting their manuscripts.

### Advertising Information

Advertising orders and enquires may be sent to [sales@sensorsportal.com](mailto:sales@sensorsportal.com) Please download also our media kit: [http://www.sensorsportal.com/DOWNLOADS/Media\\_Kit\\_2012.pdf](http://www.sensorsportal.com/DOWNLOADS/Media_Kit_2012.pdf)



**Digital Sensors and Sensor Systems: Practical Design** will greatly benefit undergraduate and at PhD students, engineers, scientists and researchers in both industry and academia. It is especially suited as a reference guide for practitioners, working for Original Equipment Manufacturers (OEM) electronics market (electronics/hardware), sensor industry, and using commercial-off-the-shelf components, as well as anyone facing new challenges in technologies, and those involved in the design and creation of new digital sensors and sensor systems, including smart and/or intelligent sensors for physical or chemical, electrical or non-electrical quantities.



*"It is an outstanding and most completed practical guide about how to deal with frequency, period, duty-cycle, time interval, pulse width modulated, phase-shift and pulse number output sensors and transducers and quickly create various low-cost digital sensors and sensor systems ..."* (from a review)

Order online:

[http://www.sensorsportal.com/HTML/BOOKSTORE/Digital\\_Sensors.htm](http://www.sensorsportal.com/HTML/BOOKSTORE/Digital_Sensors.htm)



**[www.sensorsportal.com](http://www.sensorsportal.com)**